

> Features:

Features:

Slim and compact size


1 pole 12A; 2 pole 8A

With LED integrated in relay


With lockable test button and inspection window

Conformity with RoHS directive


Conform to IEC61810-1



Sockets selection table



PRT05-E



PRT08-E



PRU05-E



PRU08-E



PRT05-ST



PRT08-ST



Relay

JQX-14FT- □ - □ □

Coil Voltage
3~110VDC
6~220VAC
Special options

D: Diode
L: LED
T: Test button

Contact form
1,2(A: normally open, B: normally close,
C: changeover)

Series Name



Socket



Relay module

Specification


		1A, 1B, 1C	2A, 2B, 2C
Contact	Contact form	1A, 1B, 1C	2A, 2B, 2C
	Rated load Resistive (AC-1)	12A/250VAC, 30VDC	8A/250VAC, 30VDC
	Motor (AC-15)	1/3HP, 240VAC; 1/2HP, 240VAC	1/6HP, 240VAC
	Operating power(Resistive)	2500VA, 300W; 4000VA, 480W	1250VA, 150W; 2000VA, 240W
	Contact resistance(Initial)	≤50mΩ	
Material		Ag alloy	
Electrical endurance		≥10 ⁵ cycles(1800 Ops/h)	
Mechanical endurance		≥10 ⁷ cycles(18000 Ops/h)	
Pick-up voltage (23°C)		DC: ≤75% Rated voltage, AC: ≤80% Rated voltage	
Drop-out voltage (23°C)		DC: ≥10% Rated voltage, AC: ≥30% Rated voltage	
Max. Allowed voltage (25°C)		110% Rated voltage	
Insulation resistance		≥1000MΩ (500VDC)	
Coil power consumption	DC(W)	0.53	
	AC(VA)	1.0	
Operate time(at nominal voltage)		≤20ms	
Release time(at nominal voltage)		≤10ms	
Initial dielectric strength	Between contacts	1000VAC/1min (Leakage current 1 mA)	
	Between poles	1000VAC/1min (Leakage current 1 mA)	
	Between contact and coil	5000VAC/1min (Leakage current 1 mA)	
Ambient temperature		-40~+65°C	
Humidity		35%~85%RH	
Atmospheric Pressure		86~106KPa	
Shock resistance		10G(Half a wave of pulses of sine:11ms)	
Vibration resistance		10~55Hz Dual amplitude:1.5mm	
Installation mode		Plug-in terminals	
Weight		Approx. 17g	
Matched relay socket		PRU05-E PRT05-E PRT05-ST	PRU08-E PRT08-E PRT08-ST
Equivalent Product	OMRON	G2R-1-SNI	G2R-2-SNI
	Schneider	RXG12	RXG22
	Finder	46.61	46.52

Coil Specifications (23°C)


Rated voltage V.DC	3	5	6	9	12	18	24	36	48	110
Coil resistance (±10%)	17	47	68	150	270	610	1100	2440	4300	22800
Rated voltage V.AC	6	12	24	48	115	230				
Coil resistance (±10%)	16	63	240	1085	6300	23000				

Contact Specification


JQX-14FT-1C Electrical durability contacts (resistive load)




Maximum switching capacity on resistive load



JQX-14FT-2C Electrical durability contacts (resistive load)




Maximum switching capacity on resistive load




Dimensions (mm)


JQX-14FT-1C




JQX-14FT-2C




Wiring Diagrams





JQX-14FT-1C




JQX-14FT-1B




JQX-14FT-1A




JQX-14FT-2C



JQX-14FT-2B



JQX-14FT-2A



Selection manual of industrial control relay


PRT05/08-A14FT Socket



Characteristics


PRT05-A

PRT08-A

Type			PRT05-A	PRT08-A
Nominal load	Current	A	12	8
	Voltage	V	250	
Dielectric strength	Between coil and contact	V/min	4000	
	Between contacts	V/min	2500	
Max. tightening torque		Nm	1.0	
Wire size		AWG/mm ²	20-14/0.5-2.5	
Ambient temperature		°C	-35~70	
Unit weight		g	23	28
Relay,accessories Selection Table				
Plastic clip		Bus jumper		
 (included in socket)		 PR08C		


Dimensions (mm)

Dimensions (mm)




PRT05-A

PRT08-A




Bus jumper PR08C

Connection Diagrams



PRT05-A



PRT08-A

Selection manual of industrial control relay


PRT05/08-E14FT Socket



Characteristics




PRT05-E




PRT08-E



Type			PRT05-E	PRT08-E
Nominal load	Current	A	12	8
	Voltage	V	250	
Dielectric strength	Between coil and contact	V/min	4000	
	Between contacts	V/min	2500	
Max. tightening torque		Nm	1.0	
Wire size		AWG/mm ²	20-14/0.5-2.5	
Ambient temperature		°C	-35~70	
Unit weight		g	23	28


Relay,accessories Selection Table		
Socket	Plastic clip	Bus jumper
PRT05-E	 PR20L (included in socket)	 PR08C
PRT08-E		

Dimensions (mm)




PRT05-E

PRT08-E




Bus jumper PR08C

Connection Diagrams



PRT05-E




PRT08-E


Characteristics

PRT05-P 	Type			PRT05-P	PRT08-P
	Nominal load	Current	A	8	10
		Voltage	V	300	
	Dielectric strength	Between coil and contact	V/min	4000	
		Between contacts	V/min	2500	
	Ambient temperature		°C	-40~+85	
	Unit weight		g	4	


PRT08-P



Dimensions (mm)



Connection Diagrams



Characteristics



PRT05-ST



PRT08-ST




Type			PRT05-ST	PRT08-ST
Nominal load	Current	A	12	8
	Voltage	V	250	
Dielectric strength	Between coil and contact	V/min	4000	
	Between contacts	V/min	2500	
Max. tightening torque		Nm	-	
Wire size		AWG/mm ²	20-14/0.5-2.5	
Ambient temperature		°C	-40~+85	
Unit weight		g	35	43

Relay,accessories Selection Table

Socket	Plastic clip	ID tag	Module	Bus jumper
PRT05-ST				
PRT08-ST				
	PR20T	PR2P	AMD	PT01CC

Dimensions (mm)



Connection Diagrams

